

# Step-By-Step Quick Start Guide To Using Your Generator

## 1 Remove Generator From Package

## 2 Add Oil

Oil Type: SAE10W-30 Oil (Must add BEFORE first use)  
Oil Capacity: 12.0 fluid oz  
Because this generator includes Low Oil Shut Off, the generator will not start with low oil. Start out with 12.0 oz, then **fill until almost overflowing.**)

## 3 Add Fuel

Unleaded gasoline only octane rating of 87 or higher  
Maximum Capacity: 1.2 Gallon fuel tank

## 4 Start The Generator

- Use the generator OUTDOORS in a WELL VENTILATED AREA.
- DO NOT CONNECT electrical devices until AFTER the generator is started.
- Turn Engine Switch to ON
- Turn FUEL PETCOCK to ON (Figure A)
- Adjust the CHOKE to CLOSED/CHOKE position (Figure B)
- Start the generator manually with the Recoil (Pull) Start.
- Once the engine has started, GRADUALLY move the choke lever to the "RUN/OPEN" position until the engine levels off. Then let the engine run approximately 5 minutes BEFORE adding appliances or tools.
- You can now connect electrical devices.

# GEN2000

2,000 Surge / 1,400 Running Watts

**UNLEADED GASOLINE FUEL**

### GENERATOR SPECIFICATIONS:

- 3.5 HP Engine, 4 Stroke OHV
- Recoil Start
- 1.2 Gallon Fuel Tank
- Low Oil Shut Off
- UL Listed Electrical Components
- Engine Shut Off Switch
- Circuit Breaker & Power Outlets
- 1-12V DC Outlet
- 2 -120V AC Outlets
- Complies with EPA emissions
- Run time = 9 hours @ 50% load
- Decibel Rating < 68 db @ 0% load
- Warranty: 2 YEAR Limited Emissions
- Warranty: 1 YEAR Limited

**OIL IS NOT INCLUDED WITH THIS GENERATOR. IT IS SOLD SEPARATELY.**

Read and understand instruction manual before using generator.



On



Off


Fuel Petcock (Figure A)



Choke (Figure B)



Closed/Choke



Run/Open



**TOLL-FREE NATIONWIDE HELP LINE! 866-460-9436**

Need Help? Call Us First!

Monday-Friday 8:00-4:30 Central Time

Visit our website for Troubleshooting & Frequently Asked Questions

**SPORTSMAN**

[www.sportsmanseriesbrand.com/generators](http://www.sportsmanseriesbrand.com/generators)