

50 AMP

Features



POWERS HARD-WIRED CIRCUITS
no need for extension cords



Pre-wired for **QUICK AND EASY INSTALLATION**



PUSH-BUTTON change between utility and generator power



POWER SOURCE INDICATING LIGHTS
utility and generator

Accessories



POWER CORD



POWER INLET BOX

Specifications

AMPERAGE (A)	50
VOLTAGE (V)	240
ENCLOSURE RATING	NEMA 1 (Indoor)
CIRCUITS	10
BREAKERS INCLUDED	2-30A 2-pole 2-20A 1-pole 2-20A 1-pole tandem
COMPLIANCE	UL 1008 / CSA C22.2 No. 178.1



Champion's 50-Amp manual transfer switch is prewired and has 10 circuits, so you no longer need extension cords to get power from your generator into your home. The switch allows you to easily change between utility and generator power, while the LED lights indicate active power sources: utility, generator, or both.

Inside the box

INSTALLATION MANUAL
PRE-WIRED MANUAL
TRANSFER SWITCH

30 FT. (9.1 M) POWER
CORD
POWER INLET BOX

What You Need

50A 2-POLE CIRCUIT
BREAKER
NM-B ELECTRICAL WIRE
ELECTRICAL CONDUIT

CONDUIT FITTINGS
WIRE CONNECTIONS

*Specifications, descriptions and illustrations are subject to change without notice.



PACKAGE (gross)
Weight: 55.1 lb.
Size: 20.3 x 19.5 x 12 in.



PRODUCT (net)
Weight: 48.1 lb.
Size: 17.6 x 15.3 x 4.4 in.

CHAMPION POWER EQUIPMENT, INC.
www.championpowerequipment.com