

PGDA70BiSCO

7250W DUAL FUEL INVERTER GENERATOR

- Super Quiet 62 dB
- Features A Stable Sine Wave To Use With Sensitive Electronic Equipment
- Remote Control Start and Easy 1-Push Electric Start with Pull Start Back-up
- Digital Control Center Displays Hours, Voltage, Load and Frequency
- 312cc OHV 4 Cycle Engine
- 7250W Peak 6000W Rated Gas
- 6500W Peak 5500W Rated LPG
- 1X USB A Port and 1X USB C Port
- 2X 120V 20A GFCI Protected Outlets
- 1X 120V/240V 30A Twist Lock Outlet
- 1X 120V 30A RV Outlet
- Runs 8.5 Hours at 1/2 Load
- Parallel Ready (Requires Parallel Kit)
- 3.6 Gallon Fuel Tank Capacity
- Low Battery and Low Oil Shutoff
- Includes 1.6 Ah Battery, Remote Control, Wheel Kit, LPG Hose with Regulator, Oil Funnel, 10W-30 Oil (27.05 FL OZ), Operator's Manual, 1-L5-30 4-Prong Plug, 1-20A Plug, 1-30A RV Plug, Spark Plug Wrench, and Dual-Use Screw Driver



**REMOTE
CONTROL
START**

**DIGITAL
DISPLAY
CENTER**
VOLTS | AMPS | POWER | HOURS



**QUIET
OPERATION**

**PARALLEL
READY**

*Parallel Kit Required For Parallel Operation
Sold Separately*

CO-SENTRY™

*Alerts You When Carbon Monoxide
is Present with Auto Shut-Off*



3 YEAR WARRANTY

Model | PGDA70BiSCO

Model No.	PGDA70BiSCO
Gross Weight (kg / lbs.)	125 lbs.
Net Weight (kg / lbs.)	118 lbs.
Box Dimensions	26.5" x 23" x 24"
UPC	8 14726 02762 9

3
YEAR
LIMITED WARRANTY

Pulsar®